


HDA-130 | SINGLE ZONE AMPLIFIER



Single Zone Amplifier



OVERVIEW

Small but powerful, the HDA-130 Single Zone Amplifier can be placed nearly anywhere and delivers 30W x 2 of power to local zone speakers. It can also stream a local source throughout the HDA system to multiple zones and supports ducking to automatically lower the volume of music playing for paging applications and microphone use.

HIGHLIGHTS

- 30 Watts / channel @ 8 Ohms (stable down to 4 Ohms)
- 96 kHz / 24-bit streaming high-definition audio quality
- High pass & low pass filters per zone
- Each zone supports a full 5-band parametric EQ
- Audio ducking capability
- Page event support
- Store up to 10 .WAV Files in each chassis (for doorbell ring chime and/ or trigger alert chimes)
- Inputs:
 - 1 3.5mm analog inputs (adapter required for Coaxial Digital input)
 - 1 PCM TosLink Digital Input
- Outputs:
 - 1 stereo amplifier output channel
 - Single L+R preamplifier output for subwoofer applications
- Powered by 48 VDC adapter or Power Over Ethernet++ injector
- Approximately 5-inches wide x 1-inch high x 5.5-inches deep
- Wall / Joist Bracket included

*HDA-SW5 AVB Network Switch is needed when more than 1 HDA product is installed

✉ totalcontrol@urc-automation.com

🌐 www.urc-automation.com

SPECIFICATIONS

SKU

HDA-130, UPC 656787-503038

System

Total Control®

Advanced system controller and professional programming required

In the Box

HDA-130, Speaker Terminal Block, 3.5mm to RCA Cable, 48 Volt DC Adapter, Left / Right L Brackets, Rubber Feet

Dimensions

4.94" (125.4mm) W x 1.44" (36.5mm) H x 5" (127mm) D

Weight

0.75 lbs (0.34 kg)

Warranty

2 year limited USA warranty

