

HDA-8100 | MULTI-ZONE AMPLIFIER



8 Source, 8 Zone (stereo) or 16 Zone (mono) Multi-Zone Amplifier



OVERVIEW

With more zones and inputs, this powerful, flexible amplifier is the new standard in high-definition audio. The HDA-8100 Multi-Zone Amplifier provides 8 stereo amplified zone outputs or up to 16 single channel amplified mono zone outputs. Better yet, any zone can be set to stereo or two independent mono zones. It features 8 analog audio inputs with audio sensing and 2 coaxial digital inputs providing plenty of options.

HIGHLIGHTS

- 100 Watts / channel @ 8Ω; 200 Watts / channel @ 4Ω
 - 96 kHz / 24-bit streaming high-definition audio quality
 - High pass & low pass filters per zone
 - Each zone supports a full 5-band parametric EQ
 - Dolby® and DTS® 5.1 channel Downmixing (digital inputs only)
 - Audio ducking capability
 - Page event support
 - Store up to 10 .WAV Files in each chassis (for doorbell ring chime and/or trigger alert chimes)
 - Permanent zone grouping (also between multiple amplifiers)
 - Inputs:
 - RCA analog inputs with audio sensing
 - 2 Coaxial Digital inputs
 - Outputs:
 - 8 stereo amplifier output channels / 16 mono output channels (any zone can be set to stereo or two independent mono zones)
 - 2 assignable pre-amp outputs
 - Two 12 Volt triggers
 - Gigabit Ethernet Connection (Full Duplex, for Gigabit LAN only)
- *HDA-SW5 AVB Network Switch is needed when more than 1 HDA product is installed

SPECIFICATIONS

SKU

HDA-8100, UPC 656787-503007

System

Total Control®

Advanced system controller and professional programming required

In the Box

HDA-8100, Ethernet Cable, Power Cord, Rack Mount Ears

Dimensions

17.125" (434.98 mm) W x 3.875"
(98.425mm) H x 11.94" (303.2mm) D

Weight

12.8 lbs (5.8 kg)

Warranty

2 year limited USA warranty

✉ totalcontrol@urc-automation.com

🌐 www.urc-automation.com

