

MRX-4IR | IR EXTENDER



Wired/Wireless IR Extender



OVERVIEW

Compact base station receives commands from Total Control primary system controller and relays them to other devices in the system. This enables control of the integrated components (such as TVs or projectors) using integrated Total Control user interfaces. It communicates over the network via Wi-Fi or wired LAN connection.

- Delivers seamless integration for wall-mount TVs and ceiling-mount projectors
- Ideal for applications where CAT5 or a larger base station is not feasible
- Features four IR outputs and front built-in IR blaster
- Connects to network via Wi-Fi or wired LAN connection

HIGHLIGHTS

Outputs	Four IR outputs (one adjustable, three fixed)
IR Blaster	Built-in front IR blaster
Ethernet	RJ45 10/100 Mbps Ethernet Port
Power	12V external power supply

SPECIFICATIONS

SKU

MRX-4IR, UPC 656787-320048

System

Total Control® Accelerator 3

Professional programming required

In the Box

Base station, IR emitters, power adaptor, mounting hardware

Dimensions

3.7" (94mm) W x 0.9" (22.8mm) H x 2.8" (71.1mm) D

Weight

0.2 lbs. (0.09 kg)

Warranty

Please visit www.urc-automation.com/warranty-statement/

800-901-0800



www.totalcontrollite.com



©2023 Universal Remote Control, Inc. Specifications subject to change without notice. URC® and Total Control® Lite are trademarks of Universal Remote Control, Inc. All other trademarks are property of their respective owners.