



The next generation of smart device control, URC Lighting creates the perfect atmosphere for entertaining or quiet family events with a line of smart dimmers, switches and networking devices. Seamlessly launch customized experiences with intuitive lighting control and so much more. URC Lighting devices display notifications for programmed triggers like an open garage door, a triggered window sensor or an approaching delivery. With a simple touch, URC Lighting enables smart control and automation across the Total Control system.

- Reliable performance and easy Z-Wave® networking
- Robust settings for true customization
- Built in configuration button with simple touch scene control
- Colorful, customizable LED bar for visual notifications
- Available in 7 popular colors with change kit

SPECIFICATIONS

SKU	LT-3200
UPC	656787-705210
Color Change	Default Color: White Color Change Kit Available to Change Paddle Color (7 Available Colors)
RF Technology	Z-Wave® Plus [S2 Encryption]
RF Frequency	908.42 MHz
Z-Wave Chip	500 Series
Multi-Way Lighting Support	3-Way / 4-Way / 5-Way
Power	120 Volt AC
Usage	Indoor; Fan Usage: 300 Watts Maximum (Inductive Load)
Installation	Neutral Wire Required
Max Wattage	600 Watt Incandescent / 300 Watt LED / 150 Watt CFL / 1200 Watt Resistive, Max Amperage 15A Heat Sink Remove does not affect Max Wattage
Min Wattage	Neutral Wire: No Minimum Required
Dimensions	W (with 2 Heat Sinks): 2.13" / 54mm, W (with 1 Heat Sink): 2" / 51mm, W (with No Heat Sinks): 1.81" / 46mm H: 4.13" / 105mm D: 1.73" / 44mm
Weight	4 oz / 28.34g
System	Total Control® Professional Programming Required
In The Box	URC Light Switch
Sold Separately	TRF-ZW10 Required
Warranty	Please visit www.urc-automation.com/warranty

✉ totalcontrol@urc-automation.com

🌐 www.urc-automation.com

