LT-3100-WH

Smart Dimmer





The next generation of smart device control, URC Lighting creates the perfect atmosphere for entertaining or quiet family events with a line of smart dimmers, switches and networking devices. Seamlessly launch customized experiences with intuitive lighting control and so much more. URC Lighting devices display notifications for programmed triggers like an open garage door, a triggered window sensor or an approaching delivery. With a simple touch, URC Lighting enables smart control and automation across the Total Control system.

- Reliable performance and easy Z-Wave® networking
- Robust settings for true customization
- Built in configuration button with simple touch scene control
- Colorful, customizable LED bar for visual notifications
- Available in 7 popular colors with change kit

SPECIFICATIONS

| SKU | LT-3100 |
|----------------------------|---|
| UPC | 656787-705203 |
| Color Change | Default Color: White Color Change Kit Available to Change Paddle Color (7 Available Colors) |
| RF Technology | Z-Wave® Plus [S2 Encryption] |
| RF Frequency | 908.42 MHz |
| Z-Wave Chip | 500 Series |
| Multi-Way Lighting Support | 3-Way / 4-Way / 5-Way |
| Power | 120 Volt AC |
| Usage | Indoor; Do Not Use with Fans or Motors |
| Installation | Neutral and Non-Neutral Installation |
| Max Wattage | No Heat Sink Tabs Removed: 400 Watt Incandescent / 300 Watt LED / 150 Watt CFL One Side Heat Sink Tabs Removed: 300 Watt Incandescent / 200 Watt LED / 150 Watt CFL Two Sides Heat Sink Tabs Removed: 200 Watt Incandescent / 150 Watt LED / 100 Watt CFL |
| Min Wattage | Neutral Wire: No Minimum Required; Non-Neutral: Minimum 25 Watt |
| Dimensions | W (with 2 Heat Sinks): 2.13" / 54mm, W (with 1 Heat Sink): 2" / 51mm, W (with No Heat Sinks): 1.81" / 46mm H: 4.13" / 105mm D: 1.73" / 44mm |
| Weight | 4 oz / 28.34g |
| System | Total Control® Professional Programming Required |
| In The Box | URC Light Dimmer |
| Sold Separately | TRF-ZW10 Required |
| Warranty | Please visit www.urc-automation.com/warranty |





www.urc-automation.com

