

MX-490

# Complete Control® Handheld Remote



This programmable, handheld remote can directly control numerous IR devices in the home. The vibrant 2" color LCD screen, as well as the remote buttons, light up for easy use. Ultra-reliable narrow band RF with a compatible Complete Control® base station, like the MRF-350 and MRF-260, the MX-490 controls integrated A/V components through walls and cabinet doors, or even from outside. With base station, there is no need to point the remote control at components or even be in the same room. The MX-490 is capable of learning IR commands from another remote.

## SPECIFICATIONS

SKU	MX-490
UPC	656787-705258
Memory	External 64Mb
LCD	240 x 320, 2" TFT
IR Range (Line of Sight via Infrared)	30 to 50 feet, depending on the environment
RF Range (Radio Frequency)	50 to 100 feet, depending on the environment
RF Frequency	418Mhz
Batteries	4x AA Alkaline Batteries (DC 6V / 1.5V x 4EA)
Operating Temp	32 - 104 F / 0~40 °C
Dimensions	W: 2.05" / 52mm H: 8.86" / 225mm D: 1.08" / 27.5mm
Weight	7.83oz / 222g (with batteries loaded)
System	Complete Control® Hand programming, no need for software. Professional programming recommended.
In The Box	MX-490 Remote Control, 4x AA Alkaline Batteries
Warranty	Please visit <a href="http://www.urb-automation.com/warranty">www.urb-automation.com/warranty</a>
Installation	Trained and certified professional audio/video installation

✉ [completecontrol@urb-automation.com](mailto:completecontrol@urb-automation.com)

🌐 [www.urb-automation.com](http://www.urb-automation.com)

